






**DC12/24V-WS2811-RGB-10/20/30W**



**Product Specification:**

- 1) Model : 10W/20W/30 WS2811 RGB flood
- 2) Material: Die-cast aluminum
- 3) Input Voltage: DC12V
- 4) Power Efficiency: 90%
- 5) Beam Angle: 120°
- 6) Led chip: USA Bridgelux 30-45mil
- 7) Power(Single LED): 10W/20W/30W instegrated led chip
- 8) LED Qty:1pcs high power led
- 9) Control:WS2811 SPI
- 10) Signal Line:With IP66 waterproof terminal connect
- 11) red wire: DC12-24V+  
blue wire: GND  
yellow wire: DAT
- 12) IP Code: IP66
- 13) Temperature:-30~50
- 14) Humidity:10%-90%RH
- 15) Lifespan:>35000hrs








### Electric wire

Comes with replacmant light source  
International powe cord, convenient wiring.  
No wiring required

### Product Description:

The product does not include controller and power supply.

1. Adopting to high power integrated RGB LED, which ensures light is more uniform, light efficiency is higher.
2. Standard WS2811 SPI signal input, external control.
3. Built-in 350mA constant current driver design to ensure light for a stable work
4. Using high transmittance tempered glass, transmittance 93%
5. Complying with ROHS, absolutely not contain mercury or other harmful substance
6. Lifespan is over 35000 hours
7. May realize "online address programing"



**WARNING**  
 Don't directly touch the wall or ceiling. You need to keep a proper distance to ensure ventilation and ensure that the lamp can dissipate heat.

1. DC12V-24V input, WS2811 led full color pixel RGB flood light, led addressable pixel floodlight. The product does not include controller and power supply.
2. Heat-resistant and rainproof Solid housing with qualified aluminum material and excellent heat dissipation. IP66 dust proof and waterproof, it works perfectly in rain, sleet and snow.
3. Easy to install-The wire length is about 15-20CM water-proof wire. need WS2811 controller +DC12-24V power supply To use., 180° adjustable lamp body make it can be installed on the ceiling, wall, ground, etc.
4. How to control the lights -Connect WS2811 controller and DC12-24V power supply, each led addressable pixel floodlight, Please do NOT put it into water while.
5. After-sales service: We provide 18 months warranty. Do not hesitate to get in touch us if you have any dissatisfaction about the quality or installation. 20-30 lamps need front and back power supply.

**4th Floor, Building C, No. 47, Baoshi East Road, Shuitian Community, Shiyan Street, Baoan District, Shenzhen, Guangdong, China**